

AGT 7201 HSB GENERATOR DE CURENT MONOFAZAT



ALTERNATOR

| | |
|-------------------|--------------------------------|
| Tip: | Sincron, monofazat, fara perii |
| Putere maxima: | 6,0 kVA |
| Factor de putere: | 1 |

MOTOR

| | |
|------------------------|--|
| Tip: | OHV, un cilindru, 4 timpi, racire cu aer |
| Model: | GX 390 |
| Capacitate cilindrica: | 389 cm ³ |
| Putere maxima: | 13,0 HP |
| Combustibil: | Benzina fara plumb |
| Capacitate rezervor: | 6,1 l |
| Masa: | 31,0 kg |
| Pornire: | La sfoara |
| Consum: | 313 g/kWh |

HONDA



HONDA
ENGINES

GRUP GENERATOR

| | |
|------------------------|---------------------------|
| Tensiune: | 230 V |
| Frecventa: | 50 Hz |
| Putere maxima: | 6,0 kVA |
| Turatie: | 3.000 rpm |
| Dimensiuni de gabarit: | 750x540x550 mm(L x l x h) |
| Masa: | 70 kg |

| | |
|-------------------|---|
| Dotari standard: | O priza monofazata schuko 16A O priza monofazata CEE 32A Protectie termic Protectie lipsă ulei Contor ore functionare |
| Dotari optionale: | Sistem de roti si manere Alternator tip AVR |